

## R2 Receiver: Garage Door Piggyback



The R2 receiver, used in combination with the GTX4 transmitters, is suitable for the remote control of electrical equipment such as gate control units and similar automations. The receiver has two outputs with normally open (NO) relay contact. When the transmitter sends a signal that is recognized as valid, the receiver causes the activation of the corresponding output relay (the contact closes). The relay will deactivate as soon as the transmitter stops sending the radio signal.

## **Easy instructions** for Memorization (or programming) the Mhouse Receiver (R2)

### Using Only 1 of the N.O. Outputs (White Wires)

The large circle in the center of the receiver is a button. Press and release the button. The LED beside it will begin to flash red. Then within 10 seconds, press and hold the button that you wish to program on the remote for approximately three seconds until the red light on the receiver flashes slowly 3 times, then let go. The red light will continue to flash for a few seconds.

Once the red light has stopped flashing you can use the remote.

### Using the 2<sup>nd</sup> N.O. Contact to Operate Another Connected Device (Purple Wires)

Press and release the large button in the center of the receiver **twice**. The LED beside it will begin to flash red, twice every second. Then within 10 seconds, press and hold the button that you wish to program on the remote for approximately three seconds until the red light on the receiver flashes slowly 3 times, then let go. The red light will continue to flash for a few seconds.

Once the red light has stopped flashing you can use the remote.

Help Line: Phone 1800 241 733